



ENGINEERING & MANAGEMENT EXAMINATIONS, JUNE - 2007
ELECTROMAGNETIC WAVES & RADIATING SYSTEMS
SEMESTER - 4

Time : 3 Hours]

[Full Marks : 70

Group - A**(Multiple Choice Type Questions)**

1. Choose the correct alternatives for any ten of the following :

10 × 1 = 10

i) The magnetic flux density \vec{B} and vector potential \vec{A} are related as

a) $\vec{B} = \nabla \times \vec{A}$

b) $\vec{A} = \nabla \times \vec{B}$

c) $\vec{B} = \nabla \cdot \vec{A}$

d) $\vec{A} = \nabla \cdot \vec{B}$

ii) A potential field is given by $V = 3x^2y - yz$. The electric field at $P(2, -1, 4)$ is

a) $12\vec{i} - 8\vec{j}$ V/m

b) $12\vec{i} - \vec{j}$ V/m

c) $12\vec{i} + 8\vec{j} + \vec{k}$ V/m

d) $-12\vec{i} - 8\vec{j} - \vec{k}$ V/m.

iii) The electric field lines & equipotential lines

a) are parallel to each other

b) are one and the same

c) cut each other orthogonally

d) can be inclined to each other at any angle. iv) A transmission line of length $\frac{\lambda}{4}$ shorted at far end behaves like

a) series resonant circuit

b) parallel resonant circuit

c) pure inductor

d) pure capacitor. v) Maxwell's equation $\nabla \times \vec{H} = \vec{J} + \frac{\partial \vec{D}}{\partial t}$ represents

a) Gauss's law in magnetism

b) Kirchhoff's current law for direct current

c) Biot-Savart law

d) Generalized Ampere's circuital law. **24506-(IV)-B**

- 24506-(IV)-B**

**Group - B****(Short Answer Type Questions)**

Answer any three questions.

3 × 5 = 15

2. Define the term i) VSWR and ii) 'Reflection co-efficient' for transmission line.

Explain the relationship between them.

3. Prove that $\nabla \times \vec{H} = \vec{J} + \frac{\partial \vec{D}}{\partial t}$. The symbols have usual meaning.

4. A 2m long lossless transmission line has an impedance of 300Ω . The velocity of propagation is 2.5×10^8 m/s. The load has an impedance of 300Ω with sending end voltage being 60V at 100 MHz. Find :

- a) The phase constant
- b) The load voltage
- c) The load current
- d) The load reflection coefficient &
- e) Standing wave ratio.

5. Why is ionosphere important for radiowave propagation ? Describe the different layers of ionosphere.

6. What do you mean by magnetic vector potential ? Write down the Maxwell's equations for time varying electromagnetic fields, when the medium is lossless, linear, isotropic, homogeneous and source free.

3 + 2

**Group - C****(Long Answer Type Questions)**Answer any *three* questions. $3 \times 15 = 45$

7. a) Find the expression of Radiation resistance of a short electric dipole with uniform current distribution. 7
- b) Define complex Poynting vector. 3
- c) Explain the concept of skin depth & find out an expression for that. 5
8. a) Derive an expression for the input impedance Z_{in} of a lossless transmission line, in terms of relevant parameters, when the line is terminated in load impedance Z_L . 6
- b) Show that for a lossless transmission line the impedance of a line repeats over every $\frac{\lambda}{2}$ distance. 5
- c) A transmission line with air as dielectric has $Z_0 = 50\Omega$ and a phase constant of 3 rad/m at 10 MHz. Find the inductance & capacitance of the line. 4
9. a) What is electromagnetic interference ? 2
- b) Why does the short wave radio signal propagate with very low attenuation at night ? Describe the sky-wave propagation of EM waves. 3 + 6
- c) What is fading ? Briefly describe the diversity techniques to reduce the effect of fading. 1 + 3
10. a) Obtain the Poynting theorem for the conservation of energy in an electromagnetic field and discuss the physical significance of each term in resulting equation. 6
- b) In free space $E(z, t) = 50 \cos(\omega t - \beta z)$ V/m. Find the average power crossing a circular area of radius 5m in the plane $x = \text{constant}$. 5
- c) Derive the equation of continuity for time varying fields. 4
11. a) State & explain Faraday's law. 4
- b) Derive the induced *emf* when a stationary loop is in the time varying B fields. 4
- c) Determine the magnetic field intensity at a point P due to a current carrying filamentary conductor AB carrying current I along Z axis with its upper and lower ends subtending angles α_1 and α_2 respectively. 7